

# Zener Diodes MM3Z2V4C - MM3Z75VC

### **Features**

- Wide Zener Voltage Range Selection, 2.4 V to 75 V
- VZ Tolerance Selection of ±5% (C Series)
- Very Small and Thin SMD Package
- Matte Tin(Sn) Finish
- These Devices are Pb-Free and are RoHS Compliant

### ABSOLUTE MAXIMUM RATINGS (T<sub>A</sub> = 25°C unless otherwise noted)

| Symbol           | Parameter                    | Value                          | Units |
|------------------|------------------------------|--------------------------------|-------|
| $P_D$            | Power Dissipation            | 200                            | mW    |
| T <sub>STG</sub> | Storage Temperature Range    | -65 to +150                    | °C    |
| $T_J$            | Maximum Junction Temperature | 150                            | °C    |
| I <sub>ZM</sub>  | Maximum Regulator Current    | P <sub>D</sub> /V <sub>Z</sub> | mA    |

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

### THERMAL CHARACTERISTICS

| Symbol         | Parameter                               | Value | Units |
|----------------|---|-------|-------|
| $R_{	heta JA}$ | Thermal Resistance, Junction to Ambient | 595   | °C/W  |

NOTE: Device mounted on PCB with minimum land pad.

### **ELECTRICAL CHARACTERISTICS**

(T<sub>A</sub> = 25°C unless otherwise specified)

| S | ymbol   | Parameter                                | Min | Тур | Max | Units    |
|---|---------|--|-----|-----|-----|----------|
|   | $V_{F}$ | Forward Voltage / I <sub>F</sub> = 10 mA | 1   | ı   | 1.0 | <b>V</b> |

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

1





SOD-323FL CASE 477AB

#### **CONNECTION DIAGRAM**



### **MARKING DIAGRAM**





### **ORDERING INFORMATION**

| Device           | Package   | Shipping†      |
|------------------|-----------|----------------|
| Refer to Product | SOD-323FL | 3,000 / Tape & |
| Table List       | (Pb-Free) | Reel           |

<sup>†</sup>For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

### MM3Z2V4C - MM3Z75VC

# **ELECTRICAL CHARACTERISTICS** ( $T_A = 25$ °C unless otherwise noted)

|             | Device         |       | V <sub>Z</sub> (V) @ I <sub>ZT</sub> |       | $Z_{ZT}(\Omega) @ I_{ZT} I_{ZT}$ (mA) |   | <b>Z</b> <sub>ZK</sub> (Ω) @ <b>I</b> <sub>ZK</sub> | I <sub>ZK</sub> (mA)   I <sub>R</sub> (μA) @ V <sub>R</sub> |       | V <sub>R</sub> (V) |
|-------------|----------------|-------|--------------------------------------|-------|---------------------------------------|---|---|---|-------|--------------------|
| Device Type | Marking        | Min.  | Тур.                                 | Max.  | Max.                                  | - | Max.  | -   | Max.  | -                  |
| MM3Z2V4C    | Z0             | 2.28  | 2.4                                  | 2.52  | 94                                    | 5 | 564   | 1   | 45    | 1                  |
| MM3Z2V7C    | Z1             | 2.57  | 2.7                                  | 2.84  | 94                                    | 5 | 564   | 1   | 18    | 1                  |
| MM3Z3V0C    | Z2             | 2.85  | 3                                    | 3.15  | 89                                    | 5 | 564   | 1   | 9     | 1                  |
| MM3Z3V3C    | Z3             | 3.14  | 3.3                                  | 3.47  | 89                                    | 5 | 564   | 1   | 4.5   | 1                  |
| MM3Z3V6C    | Z4             | 3.42  | 3.6                                  | 3.78  | 84                                    | 5 | 564   | 1   | 4.5   | 1                  |
| MM3Z3V9C    | Z5             | 3.71  | 3.9                                  | 4.1   | 84                                    | 5 | 564   | 1   | 2.7   | 1                  |
| MM3Z4V3C    | Z6             | 4.09  | 4.3                                  | 4.52  | 84                                    | 5 | 564   | 1   | 2.7   | 1                  |
| MM3Z4V7C    | <b>Z</b> 7     | 4.47  | 4.7                                  | 4.94  | 75                                    | 5 | 470   | 1   | 2.7   | 2                  |
| MM3Z5V1C    | Z8             | 4.85  | 5.1                                  | 5.36  | 56                                    | 5 | 451   | 1   | 1.8   | 2                  |
| MM3Z5V6C    | <b>Z</b> 9     | 5.32  | 5.6                                  | 5.88  | 37                                    | 5 | 376   | 1   | 0.9   | 2                  |
| MM3Z6V2C    | ZA             | 5.89  | 6.2                                  | 6.51  | 9                                     | 5 | 141   | 1   | 2.7   | 4                  |
| MM3Z6V8C    | ZB             | 6.46  | 6.8                                  | 7.14  | 14                                    | 5 | 75  | 1   | 1.8   | 4                  |
| MM3Z7V5C    | ZC             | 7.11  | 7.5                                  | 7.86  | 14                                    | 5 | 75  | 1   | 0.9   | 5                  |
| MM3Z8V2C    | ZD             | 7.79  | 8.2                                  | 8.61  | 14                                    | 5 | 75  | 1   | 0.63  | 5                  |
| MM3Z9V1C    | ZE             | 8.65  | 9.1                                  | 9.56  | 14                                    | 5 | 94  | 1   | 0.45  | 6                  |
| MM3Z10VC    | ZF             | 9.5   | 10                                   | 10.5  | 18                                    | 5 | 141   | 1   | 0.18  | 7                  |
| MM3Z11VC    | ZG             | 10.45 | 11                                   | 11.55 | 18                                    | 5 | 141   | 1   | 0.09  | 8                  |
| MM3Z12VC    | ZH             | 11.4  | 12                                   | 12.6  | 23                                    | 5 | 141   | 1   | 0.09  | 8                  |
| MM3Z13VC    | ZJ             | 12.35 | 13                                   | 13.65 | 28                                    | 5 | 160   | 1   | 0.09  | 8                  |
| MM3Z15VC    | ZK             | 14.25 | 15                                   | 15.75 | 28                                    | 5 | 188   | 1   | 0.045 | 10.5               |
| MM3Z16VC    | ZL             | 15.2  | 16                                   | 16.8  | 37                                    | 5 | 188   | 1   | 0.045 | 11.2               |
| MM3Z18VC    | ZM             | 17.1  | 18                                   | 18.9  | 42                                    | 5 | 212   | 1   | 0.045 | 12.6               |
| MM3Z20VC    | ZN             | 19    | 20                                   | 21    | 51                                    | 5 | 212   | 1   | 0.045 | 14                 |
| MM3Z22VC    | ZP             | 20.9  | 22                                   | 23.1  | 51                                    | 5 | 235   | 1   | 0.045 | 15.4               |
| MM3Z24VC    | ZR             | 22.8  | 24                                   | 25.2  | 65                                    | 5 | 235   | 1   | 0.045 | 16.8               |
| MM3Z27VC    | ZS             | 25.65 | 27                                   | 28.35 | 75                                    | 2 | 282   | 0.5   | 0.045 | 18.9               |
| MM3Z30VC    | ZT             | 28.5  | 30                                   | 31.5  | 75                                    | 2 | 282   | 0.5   | 0.045 | 21                 |
| MM3Z33VC    | ZU             | 31.35 | 33                                   | 34.65 | 75                                    | 2 | 306   | 0.5   | 0.045 | 23                 |
| MM3Z36VC    | ZV             | 34.2  | 36                                   | 37.8  | 84                                    | 2 | 329   | 0.5   | 0.045 | 25.2               |
| MM3Z39VC    | ZW             | 37.05 | 39                                   | 40.95 | 122                                   | 2 | 329   | 0.5   | 0.045 | 27.3               |
| MM3Z43VC    | ZX             | 40.85 | 43                                   | 45.15 | 141                                   | 2 | 353   | 0.5   | 0.045 | 30.1               |
| MM3Z47VC    | ZY             | 44.65 | 47                                   | 49.35 | 160                                   | 2 | 353   | 0.5   | 0.045 | 33                 |
| MM3Z51VC    | Z_             | 48.45 | 51                                   | 53.55 | 169                                   | 2 | 376   | 0.5   | 0.045 | 35.7               |
| MM3Z56VC    | Z <sub>=</sub> | 53.2  | 56                                   | 58.8  | 188                                   | 2 | 400   | 0.5   | 0.045 | 39.2               |
| MM3Z62VC    | Z₌             | 58.9  | 62                                   | 65.1  | 202                                   | 2 | 423   | 0.5   | 0.045 | 43.4               |
| MM3Z68VC    | Z>             | 64.6  | 68                                   | 71.4  | 226                                   | 2 | 447   | 0.5   | 0.045 | 47.6               |
| MM3Z75VC    | Z<             | 71.25 | 75                                   | 78.75 | 240                                   | 2 | 470   | 0.5   | 0.045 | 52.5               |

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

### TYPICAL PERFORMANCE CHARACTERISTICS

The Zener Voltage (V<sub>Z</sub>) is tested under pulse condition of 10 ms.
 The device numbers listed have a standard tolerance on the nominal zener voltage of ±5%.

<sup>3.</sup> The zener impedance is derived from the 60-cycle ac voltage, which results when an ac current having an rms value equal to 10% of the dc zener current ( $I_{ZT}$  or  $I_{ZK}$ ) is superimposed to  $I_{ZT}$  or  $I_{ZK}$ .

### MM3Z2V4C - MM3Z75VC




Figure 1. Zener Current vs. Zener Voltage




Figure 3. MM3Z3V6B Zener Current vs. Zener Voltage

I<sub>7</sub> - Zener Current, [mA]




Figure 5. MM3Z11VB Zener Current vs. Zener Voltage




Figure 2. Zener Current vs. Zener Impedance




Figure 4. MM3Z6V8B
Zener Current vs. Zener Voltage




Figure 6. MM3Z24VB Zener Current vs. Zener Voltage

## MM3Z2V4C - MM3Z75VC

## **TYPICAL PERFORMANCE CHARACTERISTICS**





Figure 7. MM3Z36VB Zener Current vs. Zener Voltage








SOD-323FL CASE 477AB ISSUE A

**DATE 03 FEB 2023** 










### NOTES:

- DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 1994.
- 2. CONTROLLING DIMENSION: MILLIMETERS
- 3. LEAD THICKNESS INCLUDES LEAD FINISH.
- 4. DIMENSIONS D AND E DO NOT INCLUDE MOLD FLASH, PROTRUSIONS, OR GATE BURRS.

|     | MILLIM |      |      |
|-----|--------|------|------|
| DIM | MIN.   | NDM  | MAX. |
| Α   | 0.60   | 0.70 | 0.90 |
| A1  | 0.00   | 0.05 | 0.10 |
| b   | 0.25   | 0.30 | 0.35 |
| c   | 0.05   | 0.10 | 0.20 |
| D   | 1.60   | 1.70 | 1.80 |
| Ε   | 1.15   | 1.25 | 1.35 |
| HE  | 2.30   | 2.50 | 2.70 |
| L   | 0.35   | 0.45 | 0.55 |



# RECOMMENDED MOUNTING FOOTPRINT

\* For additional information on our Pb-Free strategy and soldering details, please download the DN Semiconductor Soldering and Mounting Techniques Reference Manual, SDLDERRM/D.

| DOCUMENT NUMBER: | 98AON79864E | Electronic versions are uncontrolled except when accessed directly from the Document Repositor<br>Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red. |             |  |  |
|------------------|-------------|---|-------------|--|--|
| DESCRIPTION:     | SOD-323FL   |   | PAGE 1 OF 1 |  |  |

onsemi and ONSEMI are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make changes without further notice to any products herein. onsemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. onsemi does not convey any license under its patent rights nor the rights of others.

onsemi, Onsemi, and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi's product/patent coverage may be accessed at <a href="www.onsemi.com/site/pdf/Patent-Marking.pdf">www.onsemi.com/site/pdf/Patent-Marking.pdf</a>. Onsemi reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using onsemi products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by onsemi. "Typical" parameters which may be provided in onsemi data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. onsemi does not convey any license under any of its intellectual property rights nor the rights of others. onsemi products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA class 3 medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase

#### ADDITIONAL INFORMATION

**TECHNICAL PUBLICATIONS:** 

 $\textbf{Technical Library:} \ \underline{www.onsemi.com/design/resources/technical-documentation}$ 

onsemi Website: www.onsemi.com

ONLINE SUPPORT: www.onsemi.com/support

For additional information, please contact your local Sales Representative at

www.onsemi.com/support/sales