

### 20W Single Output Switching Power Supply

## LPC-20 series

User's Manual

▣᠁ᡁ

rænæn

- Features :
- Constant current design
- Universal AC input / Full range
- Withstand 300VAC surge input for 5 seconds
- Protections: Short circuit / Over voltage
- Cooling by free air convection
- · Small and compact size
- Fully encapsulated with IP67 level (Note.7)
- · Fully isolated plastic case
- Class  ${\rm I\hspace{-0.1em}I}$  power unit, no FG
- Class 2 power unit
- Pass LPS
- Suitable for LED related fixture or appliance (such as LED Decoration or Advertisement devices)(Note.10)
- 100% full load burn-in test
- Low cost, high reliability
- 2 years warranty



	LPC-20-350	LPC-20-700	
RATED CURRENT	350mA	700mA	
		9~30V	
		21W	
		200mVp-p	
. ,		F	
	±5.0%		
	±1.0% ±2.0%		
	50ms/230VAC 16ms/115VAC at full load		
	COLD START 70A(twidth=220µs measured at 50% Ipeak) at 230VAC		
MAX. No. of PSUs on 16A	8 units (circuit breaker of type B) / 14 units (circuit breaker of type C) at 230VAC		
	0.25m4/240\/AC		
		31.5 ~ 40.5V	
PROTECTION OVER VOLTAGE			
	′ -40 ~ +80°C, 10 ~ 95% RH		
VIBRATION	10 ~ 500Hz, 2G 10min./1cycle, period for 60min. each along X, Y, Z axes UL879, UL1310, CSA C22.2 No. 207-M89(except for LPC-20-350), CAN/CSA C22.2 No. 223-M91(except for LPC-20-350)		
SAFETY STANDARDS	IEC/BS EN/EN 62368-1, EAC TP TC 004, IP67 approved		
	I/P-O/P:3KVAC		
ISOLATION RESISTANCE	I/P-O/P:>100M Ohms / 500VDC / 25°C/ 70% RH		
EMC EMISSION	Compliance to BS EN/EN55032 (CISPR32) Class B, BS EN/EN61000-3-2 Class A, BS EN/EN61000-3-3, EAC TP TC 020		
EMC IMMUNITY		IS EN/EN55035, light industry level, EAC TP TC 020	
MTBF	* *	e) ;  700.1K hrs min.   MIL-HDBK-217F (25°C)	
DIMENSION			
PACKING	0.1		
<ol> <li>Ripple &amp; noise are measured</li> <li>Tolerance : includes set up to</li> <li>Derating may be needed und</li> <li>The power supply is consider complete installation, the final (as available on https://www.r</li> <li>Length of set up time is meas</li> <li>Suitable for indoor use or out</li> <li>The ambient temperature der</li> <li>For any application note and https://www.meanwell.com/Up</li> </ol>	at 20MHz of bandwidth by using a 12 <sup>°</sup> twisted pair lerance, line regulation and load regulation. ler low input voltage. Please check the static charac red as a component that will be operated in combina l equipment manufacturers must re-qualify EMC Dir meanwell.com//Upload/PDF/EMI_statement_en.pdf) sured at first cold start. Turning ON/OFF the power door use without direct sunlight exposure. Please ar ating of 3.5°C/1000m with fanless models and of 5° IP water proof function installation caution, please re pload/PDF/LED_EN.pdf	wire terminated with a 0.1 uf & 47 uf parallel capacitor. teristics for more details. tition with final equipment. Since EMC performance will be affected by the ective on the complete installation again. supply may lead to increase of the set up time. <i>v</i> oid immerse in the water over 30 minute. C/1000m with fan models for operating altitude higher than 2000m(6500ft). ofer our user manual before using.	
	VOLTAGE TOLERANCE Note.3         CURRENT ACCURACY         LINE REGULATION         LOAD REGULATION         SETUP, RISE TIME Note.6         HOLD UP TIME (Typ.)         VOLTAGE RANGE Note.4         FREQUENCY RANGE         EFFICIENCY (Typ.)         AC CURRENT (Typ.)         MAX. No. of PSUs on 16A         CIRCUIT BREAKER         LEAKAGE CURRENT         OVER VOLTAGE         WORKING TEMP.         WORKING HUMIDITY         STORAGE TEMP., HUMIDITY         TEMP. COEFFICIENT         VIBRATION         SAFETY STANDARDS         WITHSTAND VOLTAGE         ISOLATION RESISTANCE         EMC EMISSION         EMC IMMUNITY         MTBF         DIMENSION         PACKING         1. All parameters NOT specially         2. Ripple & noise are measured         3. Tolerance : includes set up tor         5. The power supply is consider         Complete installation, the fina         (as available on https://www.         6. Length of set up time is meas         7. Suitable for indoor use or out         8. The ambient temperature der         9. For any application note and https://www.meanwell.	RATED CURRENT       350mA         DC VOLTAGE RANGE       9 ~ 48V         RATED POWER       16.8W         RIPPLE & NOISE (max.) Note.2 200mVp-p         VOLTAGE TOLERANCE Note.3 ±5.0%         CURRENT ACCURACY       ±5.0%         LINE REGULATION       ±1.0%         LOAD REGULATION       ±1.0%         LOAD REGULATION       ±2.0%         SETUP, RISE TIME       Note.6         YOLTAGE RANGE       Note.6         YOLTAGE RANGE       127 ~ 370VDC         FREQUENCY RANGE       47 ~ 63Hz         EFFICIENCY (Typ.)       83%         AC CURRENT (Typ.)       0.55A/115VAC         OLD START 70A(twidth=220µs measured at 50%         MAX. No. of PSUs on 16A       8 units (circuit breaker of type B) / 14 units (circuit         IEAKAGE CURRENT       0.25mA/ 240VAC         OVER VOLTAGE       50.4 - 60V         VORKING TEMP.       -30~ +70°C (Refer to "Derating Curve")         WORKING TEMP.       -30~ +70°C (Refer to "Derating Curve")         WORKING TEMP.       -40~ +80°C, 10 - 95% RH         TEMP. COEFFICIENT       ±0.03%/PL on-condensing         STORAGE TEMP, HUMIDITY       20 - 90% RH non-condensing         STORAGE TEMP, HUMIDITY       40 - +80°C, 10 - 95% RH         TE	



#### GTIN CODE

**SPECIFICATION** 

MW Search: https://www.meanwell.com/serviceGTIN.aspx



### 20W Single Output Switching Power Supply

# LPC-20 series

